

## Outdoor Bell Box BX-7, BX-8 & BXA-8

**Battery-operated**, completely wire-free operation with a 3-year battery life guarantee. BX-7/8 is innovated with a sounder and strobe light for outdoor use to attract attention.



You are free to choose one of the following **two options for its application**:

- a) Working as part of a wireless Home Security System. The Bell Box receives signals sent from the Control Panel during alarm activation and responds by activating its siren & strobe light.
- b) Working as a local Security Alarm System. You can install up to 10 devices. Operation of the system can be controlled by the Remote Controller or the Remote Keypad. Upon receiving signals directly sent from a detector that is triggered, the Bell Box responds by activating its siren & strobe light. (Only for BX-8 & BXA-8)

### Features:

- Waterproof & UV Proof with **IP rating X3**
- Battery operated with life expectancy of > 3 years in a typical domestic environment
- Low Battery detection
- Tamper protection protects the enclosure from being opened or removed from its mounting surface
- **Jamming Detection** to protect from unauthorized interference
- System Status Indicator with siren beeps and strobe light
- Automatic Siren Cut-Off at selectable durations of 3 / 5 / 10 minutes
- Strobe Light Control can be selectable between Auto Cut-off or Manual Cut-off

## Specifications:

- Power: Alkaline D batteries x 4
- Battery life: 2 years or over<sup>1</sup>
- Siren output: 104dB @ 1 meter
- Radio frequency available: BX-7: 433 MHz  
BX-8: 868.6375 MHz Narrow FM  
BXA-8: 868.35 MHz
- Range: 433 MHz or 868.35 MHz: over 200 meters in open space  
868.6375 MHz: over 300 meters in open space
- Operating temperature: -20° to 50°C
- Humidity: up to 95% non-condensing
- Dimensions: 287 X 202 X 67 mm

\* Note<sup>1</sup>: Battery life is calculated at an average of 2 activations per day.



Climax Technology Co., Ltd.  
Website: <http://www.climax.com.tw>  
Email: [sales@climax.com.tw](mailto:sales@climax.com.tw)