

DC-15ZW Door Contact

Sensitive Monitoring, Intelligent Networking



- Compatible with any Z-Wave devices/mesh networks
- Ideal for security and home automation applications
- Anti-tamper design

The DC-15ZW is a Z-Wave door contact that detects and reports the irregular opening and closing of doors, windows, cabinets or drawers to a control panel. Compatible with any Z-Wave devices and Z-Wave mesh networks, the DC-15ZW is ideal for security and home automation applications. It serves both as a security sensor to protect entrances and valuables and as a smart home component that activates other Z-Wave devices to perform home automation functionalities.

Powered by a pre-inserted lithium battery, the DC-15ZW transmits supervisory and low battery signals to check system integrity and indicates its fault and test mode via an LED. The DC-15ZW's anti-tamper design prevents unauthorized removal or sabotage. This easy-to-install door contact with a slim and compact design blends naturally into any home décor. Its fusion of thoughtful features makes your residence a more secure and convenient place without compromising home aesthetics in any way.

Features

- Monitors the opening/closing of doors, windows, cabinets and drawers
- Compatible with any Z-Wave devices and Z-Wave mesh networks
- Can be configured to activate other Z-Wave devices via the control panel to execute security and home automation functionalities
- Powered by a pre-inserted lithium battery
- Sends low battery and supervisory signals
- Built-in reed switch
- Anti-tamper design prevents unauthorized removal or sabotage
- LED serves as a fault and test mode indicator
- Easy installation
- Slim and compact
- Compliant with CE requirements

Specifications

Protocol	Z-Wave
Frequencies	868.42MHz(EU) 908.42MHz(US)
Battery (pre-inserted)	CR2 3V lithium batteryx 1
Battery life	2 years*
Operating temperature	-10°C to +45°C
Operating humidity	Up to 85% non-condensing
Dimensions	107 mm x32 mm x22 mm

*Battery life varies by use and configuration.